

Item	Quantity	Reference	Part
1	15	C1,C2,C5,C6,C7,C10,C11, C12,C13,C14,C19,C20,C21, C101,C102	100nF
2	7	C3,C4,C17,C18,C22,C23, C24	10nF
4	1	C16	1-20pF Trimmer
5	1	C25	470nF
6	2	C26,C27	NIET PLAATSEN
7	1	C28	22uF
8	5	C29,C30,C31,	470nF
9	3	C111,C133,C135	470pF
10	5	C112,C121,C143,C145,C154	220pF
11	2	C113,C115	1.2nF
12	1	C114	2.4nF (2 x 1200pF)
13	9	C122,C131,C153,C155,C163, C165,C174,C8,C9,C15	100pF
14	2	C123,C125	680pF
15	1	C124	1.36nF (2 x 680pF)
16	4	C132,C151,C173,C175	47pF
17	1	C134	820pF
18	1	C141	56pF
19	3	C142,C152,C161	22pF
20	1	C144	390pF
21	2	C162,C171	15pF
22	1	C164	180pF
23	1	C172	10pF
24	2	D1,D2	TS4148
25	2	D3,D4	1N5711
26	1	F1	5AMP FUSE
27	2	J1,J4	SMB
28	1	K2	SCREW-05 HEADER
29	1	K3	12 HEADER M7395V12
30	1	K4	4 HEADER M7395V04

## SDRPA25 PARTLIST.txt

31	1	L2	10uH			
32	1	L3	100uH			
33	1	L101	22uH			
34	2	L111,L112	4.08uH	T44-2	28W	0,5MM
35	2	L121,L122	2.08uH	T44-2	20W	0,5MM
36	2	L131,L132	1.17uH	T44-2	15W	0,6MM
37	1	L141	0.52uH	T44-2	10W	0,6MM
38	1	L142	0.63uH	T44-2	11W	0,6MM
39	2	L151,L152	0.42uH	T44-6	9W	0,6MM
40	1	L1	1uH			
41	2	L161,L162	0.27uH	T44-6	7W	0,7MM
42	2	L171,L172	0.15uH	T44-6	5W	0,7MM
43	2	P1,P2	5K-LIN			
44	2	P3,P4	100K LIN			
45	2	Q1,Q2	RD16HHF1	MITSUBISHI		
46	1	Q3	BC848	(niet plaatsen)		
47	1	Q4	BC858			
48	2	R1,R3	27R	(CR1206)		
49	1	R2	36R	(CR1206)		
50	3	R4,R5,R7	100R	(CR0805)		
51	1	R6	120R	(CR0805)		
52	1	R8	220R	(CR0805)		
53	4	R9,R10,R15,R16	2.2K	(CR0805)		
54	2	R11,R12	3.9K	(CR0805)		
55	4	R13,R14,R21,R22	22R	(CR0805)		
56	2	R17,R18	4.7R	(CR1206)		
57	2	R19,R20	2.2R	(CR1206)		
58	2	R27,(R28)	3.3K	(CR0805)		
59	2	R29,R31	4.7K	(CR0805)		
60	1	R30	10K	(CR0805)		
61	2	R32,R33	NIET PLAATSEN			
62	2	RY101,RY102	G5V-2-12			
63	14	RY111,RY112,RY121,RY122, RY131,RY132,RY141,RY142, RY151,RY152,RY161,RY162, RY171,RY172	G5V-1-12			

SDRPA25 PARTLIST.txt

64	1	T1	TRANSF. OUT
65	1	T2	SWR-BRIDGE
66	1	T3	NIET PLAATSEN
67	1	U2	LM78L06 (SO-8)
68	1	U3	LM78L05 (SO-8)
69	1	U4	TLC0832 (SO-8)
70	1	U101	HCT4051 (SO-16)
71	1	U102	ULN2803 (SO-18W)
72	1	U1	OPA2677 (SO-8)